NETWORK-ASSISTED GLOBAL POSITIONING SYSTEMS, METHODS AND TERMINALS INCLUDING DOPPLER SHIFT AND CODE PHASE ESTIMATES

Cross-Reference to Related Applications

This application is a continuation-in-part ("CIP") of Application Serial No. 10/074,097, filed February 12, 2002, entitled *Systems and Methods for Terrestrial Reuse of Cellular Satellite Frequency Spectrum*, which itself claims the benefit of

5   provisional Application No. 60/322,240, filed September 14, 2001, entitled *Systems and Methods for Terrestrial Re-Use of Mobile Satellite Spectrum*, both of which are assigned to the assignee of the present application, the disclosures of which are hereby incorporated herein by reference in their entirety as if set forth fully herein. This application also claims the benefit of Provisional Application No. 60/438,967, filed

10   January 9, 2003, entitled *Terrestrial Network-Assisted Global Positioning Systems, Methods and Terminals Including Doppler Shift Estimates*, assigned to the assignee of the present invention, the disclosure of which is hereby incorporated hereby by reference in its entirety as if set forth fully herein.

15   ## Field of the Invention

This invention relates to cellular wireless communications systems, methods and mobile terminals, and more particularly to cellular wireless communications systems, methods and mobile terminals that include Global Positioning System (GPS) capabilities.

20

Background of the Invention

Cellular wireless communications systems, methods and mobile terminals are widely used for voice and/or data communications. As is well known to those having skill in the art, cellular wireless communications systems, methods and mobile

25   terminals include terrestrial cellular wireless communications systems, methods and mobile terminals, and/or satellite cellular wireless communications systems, methods and mobile terminals. As used herein, the term "mobile terminal" includes cellular

and/or satellite radiotelephones with or without a multi-line display; Personal Communications System (PCS) terminals that may combine a radiotelephone with data processing, facsimile and/or data communications capabilities; Personal Digital Assistants (PDA) that can include a radio frequency transceiver and a pager,

5   Internet/intranet access, Web browser, organizer, calendar and/or a global positioning system (GPS) receiver; and/or conventional laptop and/or palmtop computers or other appliances, which include a radio frequency transceiver.

It may be desirable, and may be mandatory in the future, that mobile terminals be equipped to determine the geographical location thereof, for example, to support

10   emergency position reporting, often referred to as "E911" position reporting. One way to accomplish this result is to add a GPS receiver to a mobile terminal. As is well known to those having skill in the art, GPS is a satellite navigation system that is funded by and controlled by the U.S. Department of Defense, that provides specially coded satellite signals that can be processed in a GPS receiver, enabling the receiver

15   to compute position, velocity and/or time. A description of the GPS system may be found in the publication entitled *Global Positioning System Overview* by Peter H. Dana, 1999, the disclosure of which is hereby incorporated herein by reference in its entirety as if set forth fully herein. As used herein, the term "GPS" also includes other satellite-based systems that can be used to measure positions on the earth, such as

20   GLONASS.

GPS receivers may be expensive, increase mobile terminal size and/or consume the limited amount of battery power that is available to the mobile terminal. Accordingly, techniques have been proposed to integrate some or all of a GPS receiver into a mobile terminal. See, for example, U.S. Patents 6,424,826 to Horton et

25   al. entitled *Systems and Methods for Sharing Reference Frequency Signals Within a Wireless Mobile Terminal Between a Wireless Transceiver and a Global Positioning System Receiver*; and 6,097,974 to Camp, Jr. et al. entitled *Combined GPS and Wide Bandwidth Radiotelephone Terminals and Methods.*

Moreover, it is known that GPS receivers may suffer from latency in

30   achieving a time to first fix, due to the time that it may take for the GPS receiver to download the necessary GPS satellite ephemeris data. Accordingly, systems have been proposed to shorten the time to first fix. See, for example, U.S. Patents 6,415,154 to Wang et al. entitled *Method and Apparatus for Communicating Auxilliary Information and Location Information Between a Cellular Telephone*

Network and a Global Positioning System Receiver for Reducing Code Shift Search Time of the Receiver; 6,295,023 to Bloebaum entitled *Methods, Mobile Stations and Systems for Acquiring Global Positioning System Timing Information*; 6,169,514 to Sullivan entitled *Low-Power Satellite-Based Geopositioning System*; and 5,663,734 to Krasner entitled *GPS Receiver and Method for Processing GPS Signals*.

In-building GPS operation may be particularly challenging, because the GPS receiver may need to overcome an additional 20dB-25dB degradation in received signal-to-noise ratio due to in-building attenuation. This may produce a hundredfold or more increase in the GPS signal processing latency time, compared to an outdoor use.

Summary of the Invention

Wireless communications systems according to some embodiments of the present invention include a terrestrial wireless network that is configured to transmit wireless communications including GPS data over a satellite frequency band, and a mobile terminal that is configured to receive the wireless communications including the GPS data from the terrestrial wireless network over the satellite frequency band, and to perform pseudo-range measurements using the GPS data that is received over the satellite frequency band. Accordingly, a terrestrial wireless network that uses satellite frequency bands for terrestrial communications may be used to provide a GPS assist to mobile terminals.

In other embodiments of the present invention, the mobile terminal is further configured to transmit the pseudo-range measurements to a network operations center. In other embodiments, the network operations center is configured to determine a position of the mobile terminal using the pseudo-range measurements. In yet other embodiments, the network operations center is further configured to transmit the position of the mobile terminal to the mobile terminal. In some embodiments, the mobile terminal is configured to transmit the pseudo-range measurements to the network operations center via the terrestrial wireless network. In other embodiments, the mobile terminal is configured to transmit the pseudo-range measurements to the network operations center via a space-based component.

In still other embodiments of the present invention, a mobile terminal is configured to perform pseudo-range measurements by receiving GPS coarse/acquisition (C/A) signals from a plurality of GPS satellites, estimating Doppler

shifts in the GPS coarse acquisition (C/A) signals and estimating received code phases of the GPS C/A signals using the Doppler shifts that are estimated. The estimated received code phases and/or the estimated Doppler shifts of the GPS C/A signals, along with the time of measurement, can provide the pseudo-range measurements. In these embodiments, by using the estimated Doppler shifts to estimate the received code phases of the GPS C/A signals, reduced code searching time may be obtained. It also will be understood that the embodiments described in this paragraph may be used by mobile terminals independent of the use of a terrestrial network to transmit GPS data over a satellite frequency band, and/or may be used by standalone GPS receivers with cellular data receiving capabilities.

More specifically, mobile terminals according to some embodiments of the present invention include a receiver that is configured to receive GPS C/A signals from a plurality of GPS satellites and a processor that is configured to estimate Doppler shifts in the GPS C/A signals and to estimate received code phases of the GPS C/A signals using the Doppler shifts that are estimated. In some embodiments, the receiver is further configured to receive from a wireless network, a Doppler shift that is measured at the wireless network, and a code phase that is measured at the wireless network. The processor is further configured to estimate residual Doppler shifts in the GPS C/A signals due to mobile terminal motion, using the Doppler shift and code phase that are measured at the wireless network, and to estimate the received code phases of the GPS C/A signals using the Doppler shift that is estimated. It also will be understood that embodiments described in this paragraph may be used by mobile terminals independent of the use of a terrestrial network to transmit GPS data over a satellite frequency band, and/or may be used by GPS processors with cellular data receiving capabilities.

In particular, in some embodiments, the processor is configured to estimate the residual Doppler shifts in the GPS C/A signals due to mobile terminal motion by bandpass filtering the GPS C/A signals into frequency slices (i.e., slices in the frequency domain), despreading the slices and estimating the Doppler shifts from the frequency slices that are despread. In other embodiments, the processor is configured to bandpass filter the GPS C/A into frequency slices by frequency translating the GPS C/A signals, low pass filtering the GPS C/A signals that are frequency translated and downsampling the low pass filtered, frequency translated GPS C/A signals. In other embodiments, the processor is configured to despread the frequency slices by

4

generating an internal reference code sequence approximately matched to the code sequence used by the C/A signal, frequency translating the internal reference code sequence for each frequency slice, low pass filtering the frequency translated reference code sequences and multiplying by the downsampled low pass filtered,

5   frequency translated, GPS C/A signal slices.

In still other embodiments, the processor is configured to estimate the Doppler shifts from the frequency slices that are despread by frequency-translating the frequency slices that are despread by the Doppler shift frequency that is measured at the wireless network, to obtain the residual Doppler shift complex frequency due to

10   mobile terminal motion, transforming the despread frequency translated slice sample points to the frequency domain, converting frequency domain complex values to magnitude values and adding the magnitude values on a point-by-point basis across the frequency slices. Moreover, in still other embodiments, the processor is configured to estimate the code phases of the GPS C/A signals by removing a total

15   Doppler shift by frequency-translating the GPS C/A signals by the sum of the residual Doppler shifts that are estimated plus the Doppler shift that is measured at the wireless network, summing segments of the GPS C/A signals from which the total Doppler shift has been removed, correlating the summed segments with an internally generated code frame and determining a time offset corresponding to the location of

20   the peak magnitude squared value. Finally, in still other embodiments, the processor is configured to estimate the code phases of the GPS C/A signals by Fourier-transforming the despread slice signals to the frequency domain, determining phase angles corresponding to the estimated Doppler shift frequency for each of the slices, and determining a code phase from the phase angles.

25   In some embodiments, as described above, the wireless network is a terrestrial wireless network. In other embodiments, the terrestrial wireless network comprises a terrestrial cellular network, an ancillary terrestrial network and/or a wireless local and/or wide area network. In other embodiments, the wireless network is a satellite wireless network, and the Doppler shift and C/A code phase are measured at the

30   satellite wireless network. In some embodiments, the Doppler shift and C/A code phase that are measured at the satellite wireless network are referenced to a geographic point on the earth determined by measuring relative differences in received signal levels between adjacent spot beams at the mobile terminal. In other embodiments, the Doppler shift and C/A code phase that are measured at the satellite

wireless network are referenced to a geographic point on the earth determined by measuring path delays between the mobile terminal and a satellite gateway via at least two satellite transmission paths.

Finally, it will be understood that, although embodiments of the invention have been described above in connection with systems and mobile terminals, other embodiments of the present invention can provide cellular wireless communications methods, wireless networks and methods, and mobile terminal processing methods.

Brief Description of the Drawings

Figure 1 is a schematic diagram of cellular radiotelephone systems and methods according to embodiments of the invention.

Figure 2 is a block diagram of adaptive interference reducers according to embodiments of the present invention.

Figure 3 is a spectrum diagram that illustrates satellite L-band frequency allocations.

Figure 4 is a schematic diagram of cellular satellite systems and methods according to other embodiments of the present invention.

Figure 5 illustrates time division duplex frame structures according to embodiments of the present invention.

Figure 6 is a block diagram of architectures of ancillary terrestrial components according to embodiments of the invention.

Figure 7 is a block diagram of architectures of reconfigurable radiotelephones according to embodiments of the invention.

Figure 8 graphically illustrates mapping of monotonically decreasing power levels to frequencies according to embodiments of the present invention.

Figure 9 illustrates an ideal cell that is mapped to three power regions and three associated carrier frequencies according to embodiments of the invention.

Figure 10 depicts a realistic cell that is mapped to three power regions and three associated carrier frequencies according to embodiments of the invention.

Figure 11 illustrates two or more contiguous slots in a frame that are unoccupied according to embodiments of the present invention.

Figure 12 illustrates loading of two or more contiguous slots with lower power transmissions according to embodiments of the present invention.

Figure 13 illustrates cellular wireless communications systems and methods, including terrestrial wireless networks, mobile terminals and associated methods according to some embodiments of the present invention.

Figure 14 illustrates cellular wireless communications systems and methods, including terrestrial wireless networks, mobile terminals and associated methods according to other embodiments of the present invention.

Figure 15 is a flowchart of operations that may be performed by a mobile terminal according to some embodiments of the present invention.

Figure 16 is a flowchart of operations that may be performed by a mobile terminal according to other embodiments of the present invention.

Figure 17 is a block diagram of operations that may performed by a mobile terminal according to still other embodiments of the present invention.

Figure 18 is a block diagram illustrating detailed embodiments of Figure 17.

Figure 19 is a flowchart of operations that may be performed to estimate residual Doppler shift in embodiments of Figure 17.

Figure 20 is a frequency spectrum representation of filtering of received samples into frequency slices according to embodiments of the present invention.

Figure 21 is a block diagram illustrating additional detailed embodiments of Figure 19.

Figure 22 graphically illustrates low pass filter gold code autocorrelation peaks vs. offset chip periods according to some embodiments of the present invention.

Figure 23 is a block diagram illustrating additional detailed embodiments of Figure 19.

Figure 24 is a block diagram illustrating still other detailed embodiments of Figure 17.

Figure 25 graphically illustrates interpolation for estimating code phase according to some embodiments of the present invention.

Figure 26 is a block diagram illustrating yet other detailed embodiments of Figure 17.

Figure 27 graphically illustrates a spot beam gain pattern as a function of distance from beam center.

Figure 28 graphically illustrates an example of determining a mobile terminal location within spot beam coverage according to some embodiments of the present invention.

Figure 29 illustrates an example of an estimate of mobile terminal location using gain contours according to some embodiments of the present invention.

Figure 30 illustrates an example of geo-location using ranging from two diversity satellites according to some embodiments of the present invention

5

Detailed Description of Preferred Embodiments

The present invention now will be described more fully hereinafter with reference to the accompanying drawings, in which embodiments of the invention are shown. However, this invention should not be construed as limited to the

10 embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like numbers refer to like elements throughout.

Figure 1 is a schematic diagram of cellular satellite radiotelephone systems and methods according to embodiments of the invention. As shown in Figure 1, these

15 cellular satellite radiotelephone systems and methods 100 include at least one Space-Based Component (SBC) 110, such as a satellite. The space-based component 110 is configured to transmit wireless communications to a plurality of radiotelephones 120a, 120b in a satellite footprint comprising one or more satellite radiotelephone cells 130-130'''' over one or more satellite radiotelephone forward link (downlink)

20 frequencies f_D. The space-based component 110 is configured to receive wireless communications from, for example, a first radiotelephone 120a in the satellite radiotelephone cell 130 over a satellite radiotelephone return link (uplink) frequency f_U. An ancillary terrestrial network, comprising at least one ancillary terrestrial component 140, which may include an antenna 140a and an electronics system 140b

25 (for example, at least one antenna 140a and at least one electronics system 140b), is configured to receive wireless communications from, for example, a second radiotelephone 120b in the radiotelephone cell 130 over the satellite radiotelephone uplink frequency, denoted f'_U, which may be the same as f_U. Thus, as illustrated in Figure 1, radiotelephone 120a may be communicating with the space-based

30 component 110 while radiotelephone 120b may be communicating with the ancillary terrestrial component 140. As shown in Figure 1, the space-based component 110 also undesirably receives the wireless communications from the second radiotelephone 120b in the satellite radiotelephone cell 130 over the satellite radiotelephone frequency f'_U as interference. More specifically, a potential

interference path is shown at **150**. In this potential interference path **150**, the return link signal of the second radiotelephone **120b** at carrier frequency f'_U interferes with satellite communications. This interference would generally be strongest when $f'_U = f_U$, because, in that case, the same return link frequency would be used for space-based component and ancillary terrestrial component communications over the same satellite radiotelephone cell, and no spatial discrimination between satellite radiotelephone cells would appear to exist.

Still referring to Figure 1, embodiments of satellite radiotelephone systems/methods **100** can include at least one gateway **160** that can include an antenna **160a** and an electronics system **160b** that can be connected to other networks **162** including terrestrial and/or other radiotelephone networks. The gateway **160** also communicates with the space-based component **110** over a satellite feeder link **112**. The gateway **160** also communicates with the ancillary terrestrial component **140**, generally over a terrestrial link **142**.

Still referring to Figure 1, an Interference Reducer (IR) **170a** also may be provided at least partially in the ancillary terrestrial component electronics system **140b**. Alternatively or additionally, an interference reducer **170b** may be provided at least partially in the gateway electronics system **160b**. In yet other alternatives, the interference reducer may be provided at least partially in other components of the cellular satellite system/method **100** instead of or in addition to the interference reducer **170a** and/or **170b**. The interference reducer is responsive to the space-based component **110** and to the ancillary terrestrial component **140**, and is configured to reduce the interference from the wireless communications that are received by the space-based component **110** and is at least partially generated by the second radiotelephone **120b** in the satellite radiotelephone cell **130** over the satellite radiotelephone frequency f'_U. The interference reducer **170a** and/or **170b** uses the wireless communications f'_U that are intended for the ancillary terrestrial component **140** from the second radiotelephone **120b** in the satellite radiotelephone cell **130** using the satellite radiotelephone frequency f'_U to communicate with the ancillary terrestrial component **140**.

In embodiments of the invention, as shown in Figure 1, the ancillary terrestrial component **140** generally is closer to the first and second radiotelephones **120a** and **120b**, respectively, than is the space-based component **110**, such that the wireless communications from the second radiotelephone **120b** are received by the ancillary

terrestrial component **140** prior to being received by the space-based component **110**. The interference reducer **170a** and/or **170b** is configured to generate an interference cancellation signal comprising, for example, at least one delayed replica of the wireless communications from the second radiotelephone **120b** that are received by

5 the ancillary terrestrial component **140**, and to subtract the delayed replica of the wireless communications from the second radiotelephone **120b** that are received by the ancillary terrestrial component **140** from the wireless communications that are received from the space-based component **110**. The interference reduction signal may be transmitted from the ancillary terrestrial component **140** to the gateway **160** over

10 link **142** and/or using other conventional techniques.

Thus, adaptive interference reduction techniques may be used to at least partially cancel the interfering signal, so that the same, or other nearby, satellite radiotelephone uplink frequency can be used in a given cell for communications by radiotelephones **120** with the satellite **110** and with the ancillary terrestrial component

15 **140**. Accordingly, all frequencies that are assigned to a given cell **130** may be used for both radiotelephone **120** communications with the space-based component **110** and with the ancillary terrestrial component **140**. Conventional systems may avoid terrestrial reuse of frequencies within a given satellite cell that are being used within the satellite cell for satellite communications. Stated differently, conventionally, only

20 frequencies used by other satellite cells may be candidates for terrestrial reuse within a given satellite cell. Beam-to-beam spatial isolation that is provided by the satellite system was relied upon to reduce or minimize the level of interference from the terrestrial operations into the satellite operations. In sharp contrast, embodiments of the invention can use an interference reducer to allow all frequencies assigned to a

25 satellite cell to be used terrestrially and for satellite radiotelephone communications.

Embodiments of the invention according to Figure 1 may arise from a realization that the return link signal from the second radiotelephone **120b** at f_U generally will be received and processed by the ancillary terrestrial component **140** much earlier relative to the time when it will arrive at the satellite gateway **160** from

30 the space-based component **110** via the interference path **150**. Accordingly, the interference signal at the satellite gateway **160b** can be at least partially canceled. Thus, as shown in Figure 1, an interference cancellation signal, such as the demodulated ancillary terrestrial component signal, can be sent to the satellite gateway **160b** by the interference reducer **170a** in the ancillary terrestrial component

10

140, for example using link 142. In the interference reducer 170b at the gateway 160b, a weighted (in amplitude and/or phase) replica of the signal may be formed using, for example, adaptive transversal filter techniques that are well known to those having skill in the art. Then, a transversal filter output signal is subtracted from the

5 aggregate received satellite signal at frequency f'_U that contains desired as well as interference signals. Thus, the interference cancellation need not degrade the signal-to-noise ratio of the desired signal at the gateway 160, because a regenerated (noise-free) terrestrial signal, for example as regenerated by the ancillary terrestrial component 140, can be used to perform interference suppression.

10   Figure 2 is a block diagram of embodiments of adaptive interference cancellers that may be located in the ancillary terrestrial component 140, in the gateway 160, and/or in another component of the cellular radiotelephone system 100. As shown in Figure 2, one or more control algorithms 204, known to those having skill in the art, may be used to adaptively adjust the coefficients of a plurality of

15 transversal filters 202a-202n. Adaptive algorithms, such as Least Mean Square Error (LMSE), Kalman, Fast Kalman, Zero Forcing and/or various combinations thereof or other techniques may be used. It will be understood by those having skill in the art that the architecture of Figure 2 may be used with an LMSE algorithm. However, it also will be understood by those having skill in the art that conventional architectural

20 modifications may be made to facilitate other control algorithms.

Additional embodiments of the invention now will be described with reference to Figure 3, which illustrates L-band frequency allocations including cellular radiotelephone system forward links and return links. As shown in Figure 3, the space-to-ground L-band forward link (downlink) frequencies are assigned from 1525

25 MHz to 1559 MHz. The ground-to-space L-band return link (uplink) frequencies occupy the band from 1626.5 MHz to 1660.5 MHz. Between the forward and return L-band links lie the GPS/GLONASS radionavigation band (from 1559 MHz to 1605 MHz).

In the present application, GPS/GLONASS will be referred to simply as GPS

30 for the sake of brevity. Moreover, the acronyms ATC and SBC will be used for the ancillary terrestrial component and the space-based component, respectively, for the sake of brevity.

As is known to those skilled in the art, GPS receivers may be extremely sensitive since they are designed to operate on very weak spread-spectrum

radionavigation signals that arrive on the earth from a GPS satellite constellation. As a result, GPS receivers may to be highly susceptible to in-band interference. ATCs that are configured to radiate L-band frequencies in the forward satellite band (1525 to 1559 MHz) can be designed with very sharp out-of-band emissions filters to satisfy

5   the stringent out-of-band spurious emissions desires of GPS.

Referring again to Figure 1, some embodiments of the invention can provide systems and methods that can allow an ATC **140** to configure itself in one of at least two modes. In accordance with a first mode, which may be a standard mode and may provide highest capacity, the ATC **140** transmits to the radiotelephones **120** over the

10   frequency range from 1525 MHz to 1559 MHz, and receives transmissions from the radiotelephones **120** in the frequency range from 1626.5 MHz to 1660.5 MHz, as illustrated in Figure 3. In contrast, in a second mode of operation, the ATC **140** transmits wireless communications to the radiotelephones **120** over a modified range of satellite band forward link (downlink) frequencies. The modified range of satellite

15   band forward link frequencies may be selected to reduce, compared to the unmodified range of satellite band forward link frequencies, interference with wireless receivers such as GPS receivers that operate outside the range of satellite band forward link frequencies.

Many modified ranges of satellite band forward link frequencies may be

20   provided according to embodiments of the present invention. In some embodiments, the modified range of satellite band forward link frequencies can be limited to a subset of the original range of satellite band forward link frequencies, so as to provide a guard band of unused satellite band forward link frequencies. In other embodiments, all of the satellite band forward link frequencies are used, but the

25   wireless communications to the radiotelephones are modified in a manner to reduce interference with wireless receivers that operate outside the range of satellite band forward link frequencies. Combinations and subcombinations of these and/or other techniques also may be used, as will be described below.

It also will be understood that embodiments of the invention that will now be

30   described in connection with Figures 4-12 will be described in terms of multiple mode ATCs **140** that can operate in a first standard mode using the standard forward and return links of Figure 3, and in a second or alternate mode that uses a modified range of satellite band forward link frequencies and/or a modified range of satellite band return link frequencies. These multiple mode ATCs can operate in the second, non-

standard mode, as long as desirable, and can be switched to standard mode otherwise. However, other embodiments of the present invention need not provide multiple mode ATCs but, rather, can provide ATCs that operate using the modified range of satellite band forward link and/or return link frequencies.

5   Embodiments of the invention now will be described, wherein an ATC operates with an SBC that is configured to receive wireless communications from radiotelephones over a first range of satellite band return link frequencies and to transmit wireless communications to the radiotelephones over a second range of satellite band forward link frequencies that is spaced apart from the first range.

10 According to these embodiments, the ATC is configured to use at least one time division duplex frequency to transmit wireless communications to the radiotelephones and to receive wireless communications from the radiotelephones at different times. In particular, in some embodiments, the at least one time division duplex frequency that is used to transmit wireless communications to the radiotelephones and to receive

15 wireless communications from the radiotelephones at different times, comprises a frame including a plurality of slots. At least a first one of the slots is used to transmit wireless communications to the radiotelephones and at least a second one of the slots is used to receive wireless communications from the radiotelephones. Thus, in some embodiments, the ATC transmits and receives, in Time Division Duplex (TDD)

20 mode, using frequencies from 1626.5 MHz to 1660.5 MHz. In some embodiments, all ATCs across the entire network may have the stated configuration/reconfiguration flexibility. In other embodiments, only some ATCs may be reconfigurable.

     Figure 4 illustrates satellite systems and methods **400** according to some embodiments of the invention, including an ATC **140** communicating with a

25 radiotelephone **120b** using a carrier frequency f''_U in TDD mode. Figure 5 illustrates an embodiment of a TDD frame structure. Assuming full-rate GSM (eight time slots per frame), up to four full-duplex voice circuits can be supported by one TDD carrier. As shown in Figure 5, the ATC **140** transmits to the radiotelephone **120b** over, for example, time slot number 0. The radiotelephone **120b** receives and replies back to

30 the ATC **140** over, for example, time slot number 4. Time slots number 1 and 5 may be used to establish communications with another radiotelephone, and so on.

     A Broadcast Control CHannel (BCCH) is preferably transmitted from the ATC **140** in standard mode, using a carrier frequency from below any guard band

exclusion region. In other embodiments, a BCCH also can be defined using a TDD carrier. In any of these embodiments, radiotelephones in idle mode can, per established GSM methodology, monitor the BCCH and receive system-level and paging information. When a radiotelephone is paged, the system decides what type of

5   resource to allocate to the radiotelephone in order to establish the communications link. Whatever type of resource is allocated for the radiotelephone communications channel (TDD mode or standard mode), the information is communicated to the radiotelephone, for example as part of the call initialization routine, and the radiotelephone configures itself appropriately.

10   It may be difficult for the TDD mode to co-exist with the standard mode over the same ATC, due, for example, to the ATC receiver LNA stage. In particular, assuming a mixture of standard and TDD mode GSM carriers over the same ATC, during the part of the frame when the TDD carriers are used to serve the forward link (when the ATC is transmitting TDD) enough energy may leak into the receiver front

15   end of the same ATC to desensitize its LNA stage.

Techniques can be used to suppress the transmitted ATC energy over the 1600 MHz portion of the band from desensitizing the ATC's receiver LNA, and thereby allow mixed standard mode and TDD frames. For example, isolation between outbound and inbound ATC front ends and/or antenna system return loss may be

20   increased or maximized. A switchable band-reject filter may be placed in front of the LNA stage. This filter would be switched in the receiver chain (prior to the LNA) during the part of the frame when the ATC is transmitting TDD, and switched out during the rest of the time. An adaptive interference canceller can be configured at RF (prior to the LNA stage). If such techniques are used, suppression of the order of

25   70 dB can be attained, which may allow mixed standard mode and TDD frames. However, the ATC complexity and/or cost may increase.

Thus, even though ATC LNA desensitization may be reduced or eliminated, it may use significant special engineering and attention and may not be economically worth the effort. Other embodiments, therefore, may keep TDD ATCs pure TDD,

30   with the exception, perhaps, of the BCCH carrier which may not be used for traffic but only for broadcasting over the first part of the frame, consistent with TDD protocol. Moreover, Random Access CHannel (RACH) bursts may be timed so that they arrive at the ATC during the second half of the TDD frame. In some

embodiments, all TDD ATCs may be equipped to enable reconfiguration in response to a command.

It is well recognized that during data communications or other applications, the forward link may use transmissions at higher rates than the return link. For example, in web browsing with a radiotelephone, mouse clicks and/or other user selections typically are transmitted from the radiotelephone to the system. The system, however, in response to a user selection, may have to send large data files to the radiotelephone. Hence, other embodiments of the invention may be configured to enable use of an increased or maximum number of time slots per forward GSM carrier frame, to provide a higher downlink data rate to the radiotelephones.

Thus, when a carrier frequency is configured to provide service in TDD mode, a decision may be made as to how many slots will be allocated to serving the forward link, and how many will be dedicated to the return link. Whatever the decision is, it may be desirable that it be adhered to by all TDD carriers used by the ATC, in order to reduce or avoid the LNA desensitization problem described earlier. In voice communications, the partition between forward and return link slots may be made in the middle of the frame as voice activity typically is statistically bidirectionally symmetrical. Hence, driven by voice, the center of the frame may be where the TDD partition is drawn.

To increase or maximize forward link throughput in data mode, data mode TDD carriers according to embodiments of the invention may use a more spectrally efficient modulation and/or protocol, such as the EDGE modulation and/or protocol, on the forward link slots. The return link slots may be based on a less spectrally efficient modulation and/or protocol such as the GPRS (GMSK) modulation and/or protocol. The EDGE modulation/protocol and the GPRS modulation/protocol are well known to those having skill in the art, and need not be described further herein. Given an EDGE forward/GPRS return TDD carrier strategy, up to $(384/2) = 192$ kbps may be supported on the forward link while on the return link the radiotelephone may transmit at up to $(115/2) \approx 64$ kbps.

In other embodiments, it also is possible to allocate six time slots of an eight-slot frame for the forward link and only two for the return link. In these embodiments, for voice services, given the statistically symmetric nature of voice, the return link vocoder may need to be comparable with quarter-rate GSM, while the

15

forward link vocoder can operate at full-rate GSM, to yield six full-duplex voice circuits per GSM TDD-mode carrier (a voice capacity penalty of 25%). Subject to this non-symmetrical partitioning strategy, data rates of up to $(384)(6/8) = 288$ kbps may be achieved on the forward link, with up to $(115)(2/8) \approx 32$ kbps on the return

5   link.

Figure 6 depicts an ATC architecture according to embodiments of the invention, which can lend itself to automatic configuration between the two modes of standard GSM and TDD GSM on command, for example, from a Network Operations Center (NOC) via a Base Station Controller (BSC). It will be understood that in these

10   embodiments, an antenna **620** can correspond to the antenna **140a** of Figures 1 and 4, and the remainder of Figure 6 can correspond to the electronics system **140b** of Figures 1 and 4. If a reconfiguration command for a particular carrier, or set of carriers, occurs while the carrier(s) are active and are supporting traffic, then, via the in-band signaling Fast Associated Control CHannel (FACCH), all affected

15   radiotelephones may be notified to also reconfigure themselves and/or switch over to new resources. If carrier(s) are reconfigured from TDD mode to standard mode, automatic reassignment of the carrier(s) to the appropriate standard-mode ATCs, based, for example, on capacity demand and/or reuse pattern can be initiated by the NOC. If, on the other hand, carrier(s) are reconfigured from standard mode to TDD

20   mode, automatic reassignment to the appropriate TDD-mode ATCs can take place on command from the NOC.

Still referring to Figure 6, a switch **610** may remain closed when carriers are to be demodulated in the standard mode. In TDD mode, this switch **610** may be open during the first half of the frame, when the ATC is transmitting, and closed during the

25   second half of the frame, when the ATC is receiving. Other embodiments also may be provided.

Figure 6 assumes N transceivers per ATC sector, where N can be as small as one, since a minimum of one carrier per sector generally is desired. Each transceiver is assumed to operate over one GSM carrier pair (when in standard mode) and can

30   thus support up to eight full-duplex voice circuits, neglecting BCCH channel overhead. Moreover, a standard GSM carrier pair can support sixteen full-duplex voice circuits when in half-rate GSM mode, and up to thirty two full-duplex voice circuits when in quarter-rate GSM mode.

When in TDD mode, the number of full duplex voice circuits may be reduced by a factor of two, assuming the same vocoder. However, in TDD mode, voice service can be offered via the half-rate GSM vocoder with almost imperceptible quality degradation, in order to maintain invariant voice capacity. Figure 7 is a block

5   diagram of a reconfigurable radiotelephone architecture that can communicate with a reconfigurable ATC architecture of Figure 6. In Figure 7, an antenna **720** is provided, and the remainder of Figure 7 can provide embodiments of an electronics system for the radiotelephone.

It will be understood that the ability to reconfigure ATCs and radiotelephones

10   according to embodiments of the invention may be obtained at a relatively small increase in cost. The cost may be mostly in Non-Recurring Engineering (NRE) cost to develop software. Some recurring cost may also be incurred, however, in that at least an additional RF filter and a few electronically controlled switches may be used per ATC and radiotelephone. All other hardware/software can be common to

15   standard-mode and TDD-mode GSM.

Referring now to Figure 8, other radiotelephone systems and methods according to embodiments of the invention now will be described. In these embodiments, the modified second range of satellite band forward link frequencies includes a plurality of frequencies in the second range of satellite band forward link

20   frequencies that are transmitted by the ATCs to the radiotelephones at a power level, such as maximum power level, that monotonically decreases as a function of (increasing) frequency. More specifically, as will be described below, in some embodiments, the modified second range of satellite band forward link frequencies includes a subset of frequencies proximate to a first or second end of the range of

25   satellite band forward link frequencies that are transmitted by the ATC to the radiotelephones at a power level, such as a maximum power level, that monotonically decreases toward the first or second end of the second range of satellite band forward link frequencies. In still other embodiments, the first range of satellite band return link frequencies is contained in an L-band of satellite frequencies above GPS

30   frequencies and the second range of satellite band forward link frequencies is contained in the L-band of satellite frequencies below the GPS frequencies. The modified second range of satellite band forward link frequencies includes a subset of frequencies proximate to an end of the second range of satellite band forward link frequencies adjacent the GPS frequencies that are transmitted by the ATC to the

radiotelephones at a power level, such as a maximum power level, that monotonically decreases toward the end of the second range of satellite band forward link frequencies adjacent the GPS frequencies.

5   Without being bound by any theory of operation, a theoretical discussion of the mapping of ATC maximum power levels to carrier frequencies according to embodiments of the present invention now will be described. Referring to Figure 8, let $v = \mathcal{F}(\rho)$ represent a mapping from the power (ρ) domain to the frequency (v) range. The power (ρ) is the power that an ATC uses or should transmit in order to reliably communicate with a given radiotelephone. This power may depend on many

10   factors such as the radiotelephone's distance from the ATC, the blockage between the radiotelephone and the ATC, the level of multipath fading in the channel, etc., and as a result, will, in general, change as a function of time. Hence, the power used generally is determined adaptively (iteratively) via closed-loop power control, between the radiotelephone and ATC.

15   The frequency (v) is the satellite carrier frequency that the ATC uses to communicate with the radiotelephone. According to embodiments of the invention, the mapping $\mathcal{F}$ is a monotonically decreasing function of the independent variable ρ. Consequently, in some embodiments, as the maximum ATC power increases, the carrier frequency that the ATC uses to establish and/or maintain the communications

20   link decreases. Figure 8 illustrates an embodiment of a piece-wise continuous monotonically decreasing (stair-case) function. Other monotonic functions may be used, including linear and/or nonlinear, constant and/or variable decreases. FACCH or Slow Associated Control CHannel (SACCH) messaging may be used in embodiments of the invention to facilitate the mapping adaptively and in substantially

25   real time.

Figure 9 depicts an ideal cell according to embodiments of the invention, where, for illustration purposes, three power regions and three associated carrier frequencies (or carrier frequency sets) are being used to partition a cell. For simplicity, one ATC transmitter at the center of the idealized cell is assumed with no

30   sectorization. In embodiments of Figure 9, the frequency (or frequency set) f_1 is taken from substantially the upper-most portion of the L-band forward link frequency set, for example from substantially close to 1559 MHz (see Figure 3). Correspondingly,

the frequency (or frequency set) f_M is taken from substantially the central portion of the L-band forward link frequency set (see Figure 3). In concert with the above, the frequency (or frequency set) f_O is taken from substantially the lowest portion of the L-band forward link frequencies, for example close to 1525 MHz (see Figure 3).

5   Thus, according to embodiments of Figure 9, if a radiotelephone is being served within the outer-most ring of the cell, that radiotelephone is being served via frequency f_O. This radiotelephone, being within the furthest area from the ATC, has (presumably) requested maximum (or near maximum) power output from the ATC. In response to the maximum (or near maximum) output power request, the ATC uses

10   its a priori knowledge of power-to-frequency mapping, such as a three-step staircase function of Figure 9. Thus, the ATC serves the radiotelephone with a low-value frequency taken from the lowest portion of the mobile L-band forward link frequency set, for example, from as close to 1525 MHz as possible. This, then, can provide additional safeguard to any GPS receiver unit that may be in the vicinity of the ATC.

15   Embodiments of Figure 9 may be regarded as idealized because they associate concentric ring areas with carrier frequencies (or carrier frequency sets) used by an ATC to serve its area. In reality, concentric ring areas generally will not be the case. For example, a radiotelephone can be close to the ATC that is serving it, but with significant blockage between the radiotelephone and the ATC due to a building. This

20   radiotelephone, even though relatively close to the ATC, may also request maximum (or near maximum) output power from the ATC. With this in mind, Figure 10 may depict a more realistic set of area contours that may be associated with the frequencies being used by the ATC to serve its territory, according to embodiments of the invention. The frequency (or frequency set) f_I may be reused in the immediately

25   adjacent ATC cells owing to the limited geographical span associated with f_I relative to the distance between cell centers. This may also hold for f_M.

     Referring now to Figure 11, other modified second ranges of satellite band forward link frequencies that can be used by ATCs according to embodiments of the present invention now will be described. In these embodiments, at least one

30   frequency in the modified second range of satellite band forward link frequencies that is transmitted by the ATC to the radiotelephones comprises a frame including a plurality of slots. In these embodiments, at least two contiguous slots in the frame that is transmitted by the ATC to the radiotelephones are left unoccupied. In other embodiments, three contiguous slots in the frame that is transmitted by the ATC to the

radiotelephones are left unoccupied. In yet other embodiments, at least two contiguous slots in the frame that is transmitted by the ATC to the radiotelephones are transmitted at lower power than remaining slots in the frame. In still other embodiments, three contiguous slots in the frame that is transmitted by the ATC to the

5 radiotelephones are transmitted at lower power than remaining slots in the frame. In yet other embodiments, the lower power slots may be used with first selected ones of the radiotelephones that are relatively close to the ATC and/or are experiencing relatively small signal blockage, and the remaining slots are transmitted at higher power to second selected ones of the radiotelephones that are relatively far from the

10 ATC and/or are experiencing relatively high signal blockage.

Stated differently, in accordance with some embodiments of the invention, only a portion of the TDMA frame is utilized. For example, only the first four (or last four, or any contiguous four) time slots of a full-rate GSM frame are used to support traffic. The remaining slots are left unoccupied (empty). In these embodiments,

15 capacity may be lost. However, as has been described previously, for voice services, half-rate and even quarter-rate GSM may be invoked to gain capacity back, with some potential degradation in voice quality. The slots that are not utilized preferably are contiguous, such as slots 0 through 3 or 4 through 7 (or 2 through 5, etc.). The use of non-contiguous slots such as 0, 2, 4, and 6, for example, may be less desirable. Figure

20 11 illustrates four slots (4-7) being used and four contiguous slots (0-3) being empty in a GSM frame.

It has been found experimentally, according to these embodiments of the invention, that GPS receivers can perform significantly better when the interval between interference bursts is increased or maximized. Without being bound by any

25 theory of operation, this effect may be due to the relationship between the code repetition period of the GPS C/A code (1 msec) and the GSM burst duration (about 0.577 msec). With a GSM frame occupancy comprising alternate slots, each GPS signal code period can experience at least one "hit", whereas a GSM frame occupancy comprising four to five contiguous slots allows the GPS receiver to derive sufficient

30 clean information so as to "flywheel" through the error events.

According to other embodiments of the invention, embodiments of Figures 8-10 can be combined with embodiments of Figure 11. Furthermore, according to other embodiments of the invention, if an f_1 carrier of Figures 9 or 10 is underutilized,

because of the relatively small footprint of the inner-most region of the cell, it may be used to support additional traffic over the much larger outermost region of the cell.

Thus, for example, assume that only the first four slots in each frame of f_l are being used for inner region traffic. In embodiments of Figures 8-10, these four f_l slots are carrying relatively low power bursts, for example of the order of 100 mW or less, and may, therefore, appear as (almost) unoccupied from an interference point of view. Loading the remaining four (contiguous) time slots of f_l with relatively high-power bursts may have negligible effect on a GPS receiver because the GPS receiver would continue to operate reliably based on the benign contiguous time interval occupied by the four low-power GSM bursts. Figure 12 illustrates embodiments of a frame at carrier f_l supporting four low-power (inner interval) users and four high-power (outer interval) users. In fact, embodiments illustrated in Figure 12 may be a preferred strategy for the set of available carrier frequencies that are closest to the GPS band. These embodiments may avoid undue capacity loss by more fully loading the carrier frequencies.

The experimental finding that interference from GSM carriers can be relatively benign to GPS receivers provided that no more than, for example, 5 slots per 8 slot GSM frame are used in a contiguous fashion can be very useful. It can be particularly useful since this experimental finding may hold even when the GSM carrier frequency is brought very close to the GPS band (as close as 1558.5 MHz) and the power level is set relatively high. For example, with five contiguous time slots per frame populated, the worst-case measured GPS receiver may attain at least 30 dB of desensitization margin, over the entire ATC service area, even when the ATC is radiating at 1558.5 MHz. With four contiguous time slots per frame populated, an additional 10 dB desensitization margin may be gained for a total of 40 dB for the worst-case measured GPS receiver, even when the ATC is radiating at 1558.5 MHz.

There still may be concern about the potential loss in network capacity (especially in data mode) that may be incurred over the frequency interval where embodiments of Figure 11 are used to underpopulate the frame. Moreover, even though embodiments of Figure 12 can avoid capacity loss by fully loading the carrier, they may do so subject to the constraint of filling up the frame with both low-power and high-power users. Moreover, if forward link carriers are limited to 5 contiguous high power slots per frame, the maximum forward link data rate per carrier that may be aimed at a particular user may become proportionately less.

Therefore, in other embodiments, carriers which are subject to contiguous empty/low power slots are not used for the forward link. Instead, they are used for the return link. Consequently, in some embodiments, at least part of the ATC is configured in reverse frequency mode compared to the SBC in order to allow

5   maximum data rates over the forward link throughout the entire network. On the reverse frequency return link, a radiotelephone may be limited to a maximum of 5 slots per frame, which can be adequate for the return link. Whether the five available time slots per frame, on a reverse frequency return link carrier, are assigned to one radiotelephone or to five different radiotelephones, they can be assigned contiguously

10   in these embodiments. As was described in connection with Figure 12, these five contiguous slots can be assigned to high-power users while the remaining three slots may be used to serve low-power users.

Other embodiments may be based on operating the ATC entirely in reverse frequency mode compared to the SBC. In these embodiments, an ATC transmits over

15   the satellite return link frequencies while radiotelephones respond over the satellite forward link frequencies. If sufficient contiguous spectrum exists to support CDMA technologies, and in particular the emerging Wideband-CDMA 3G standard, the ATC forward link can be based on Wideband-CDMA to increase or maximize data throughput capabilities. Interference with GPS may not be an issue since the ATCs

20   transmit over the satellite return link in these embodiments. Instead, interference may become a concern for the radiotelephones. Based, however, on embodiments of Figures 11-12, the radiotelephones can be configured to transmit GSM since ATC return link rates are expected, in any event, to be lower than those of the forward link. Accordingly, the ATC return link may employ GPRS-based data modes, possibly

25   even EDGE. Thus, return link carriers that fall within a predetermined frequency interval from the GPS band-edge of 1559 MHz, can be under loaded, per embodiments of Figures 11 or 12, to satisfy GPS interference concerns.

Finally, other embodiments may use a partial or total reverse frequency mode and may use CDMA on both forward and return links. In these embodiments, the

30   ATC forward link to the radiotelephones utilizes the frequencies of the satellite return link (1626.5 MHz to 1660.5 MHz) whereas the ATC return link from the radiotelephones uses the frequencies of the satellite forward link (1525 MHz to 1559 MHz). The ATC forward link can be based on an existing or developing CDMA technology (e.g., IS-95, Wideband-CDMA, etc.). The ATC network return link can

also be based on an existing or developing CDMA technology provided that the radiotelephone's output is gated to cease transmissions for approximately 3 msec once every T msec. In some embodiments, T will be greater than or equal to 6 msec.

5   This gating may not be needed for ATC return link carriers at approximately 1550 MHz or below. This gating can reduce or minimize out-of-band interference (desensitization) effects for GPS receivers in the vicinity of an ATC. To increase the benefit to GPS, the gating between all radiotelephones over an entire ATC service area can be substantially synchronized. Additional benefit to GPS may be derived from system-wide synchronization of gating. The ATCs can instruct all active

10   radiotelephones regarding the gating epoch. All ATCs can be mutually synchronized via GPS.

Network-Assisted Global Positioning Systems, Methods and Terminals Including Doppler Shift Estimates

15   Figure 13 illustrates cellular wireless communications systems and methods, including wireless networks, mobile terminals and associated methods according to some embodiments of the present invention. As shown in Figure 13, these cellular wireless communications systems and methods may communicate with one or more mobile terminals 1310 via a plurality of cells 1330 served by a terrestrial wireless

20   network that includes a plurality of terrestrial base stations 1320. Although only one cell 1330 is shown in Figure 13, a typical cellular wireless communications system/method may comprise hundreds of cells and may serve thousands of mobile terminals 1310. It also will be understood by those having skill in the art that, in some embodiments of the present invention, the cells 1330 may correspond to cells of

25   an Ancillary Terrestrial Network (ATN), as were described in the preceding section, the terrestrial base stations 1320 may correspond to an Ancillary Terrestrial Component (ATC) 140 in an ancillary terrestrial network, as was described in the preceding section, and the mobile terminals 1310 may correspond to a radiotelephone 120, as was described in the preceding section.

30   Still referring to Figure 13, the terrestrial wireless network including the plurality of cells 1330 and the plurality of terrestrial base stations 1320, are configured to transmit wireless communications including GPS data 1322 over a satellite frequency band F_s, such as one or more portions of the L-band satellite frequency spectrum illustrated in Figure 3. In some embodiments, the satellite

23

frequency band F_s is outside the GPS frequency band illustrated in Figure 3. The mobile terminal **1310** is configured to receive the wireless communications including the GPS data **1322** from the terrestrial wireless network, including the terrestrial base station **1320**, over the satellite frequency band F_s, for example using a receiver of a

5   transceiver (transmitter/receiver) **1314**. The mobile terminal **1310** also is configured to receive GPS signals **1342** from a plurality, shown in Figure 13 as three, of GPS satellites **1340**. The mobile terminal **1310** also is configured to perform pseudo-range measurements using the GPS signals **1342** that are received from the GPS satellites **1340** and the GPS data **1322** that is received over the satellite frequency band F_s, for

10   example, using a processor **1316**. Accordingly, a satellite frequency band is used terrestrially to provide GPS assist to a mobile terminal. It also will be understood that, in some embodiments, the terrestrial base station **1320** is a terrestrial base station of a conventional terrestrial cellular communications system that uses at least one satellite frequency band F_s for transmission.

15   Figure 14 illustrates cellular wireless communications systems and methods including wireless networks, mobile terminals and associated methods according to other embodiments of the present invention. Referring now to Figure 14, these embodiments of the present invention also include a network operations center (NOC) **1454** that is connected to the terrestrial base stations **1320**, either directly or via one or

20   more intermediary network elements, such as a Mobile Telephone Switching Office (MTSO). As shown in Figure 14, in some embodiments, the mobile terminal **1310** is further configured to transmit the pseudo-range measurements **1312** to the network operations center **1454** via the terrestrial base station **1320**, using a terrestrial cellular frequency band, a satellite cellular frequency band and/or any other frequency band.

25   The network operations center **1454** is configured to receive the pseudo-range measurements **1312**, and to determine a position of the mobile terminal **1310** using the pseudo-range measurements **1312**. Accordingly, in some embodiments, as shown in Figure 14, the mobile terminal **1310** is configured to transmit the pseudo-range measurements **1312** to the network operation center **1454** via the terrestrial wireless

30   network, including the terrestrial base stations **1320**.

In still other embodiments of the present invention, as also illustrated in Figure 14, a space-based component **1450** also is included that is configured to wirelessly communicate with the mobile terminal **1310** over the satellite frequency band F_s. A feeder link **1456** is used for communications between the space-based component

1450 and a gateway **1452**. The gateway **1452** may be connected to the network operations center **1454** either directly or via one or more intermediary network elements. A service link also is provided for transmission from the space-based component **1450** to the mobile terminal **1310** via a forward service link **1458a**, and to

5   receive communications from the mobile terminal **1310** via a return service link **1458b**. Moreover, in some embodiments, the mobile terminal is configured to transmit the pseudo-range measurements to the network operation center **1454** via the return service link **1458b**, the space-based component **1450**, the feeder link **1456**, and the gateway **1452**. In still other embodiments, combinations of the terrestrial base

10   stations **1320** and the space-based component **1450** may be used to receive the pseudo-range measurements from the mobile terminal **1310** and to transmit the pseudo-range measurements to the network operations center **1454**.

Figure 15 is a flowchart of operations that may be performed by a mobile terminal, such as a mobile terminal **1310** of Figures 13 or 14, to provide terrestrial

15   wireless network-assisted GPS measurements. It will be understood by those having skill in the art that these operations may be performed, for example, by the radio frequency transceiver **1314** and the processor **1316** that is included in mobile terminals **1310**.

It also will be understood by those having skill in the art that the operations of

20   Figure 15 may be performed based on GPS data from a wireless network that may be a terrestrial and/or satellite wireless network using terrestrial and/or satellite frequency bands. Accordingly, embodiments of the present invention that are described in Figure 15 may be performed independent of the use of a satellite frequency band by a terrestrial wireless network, to convey GPS data to the mobile

25   terminal.

Referring now to Figure 15, at Block **1510**, GPS C/A signals are received at the mobile terminal such as the mobile terminal **1310**, for example as part of the GPS signals **1342** that are received from the plurality of GPS satellites **1340**. At Block **1520**, the processor of the mobile terminal, such as the processor **1316** of the mobile

30   terminal **1310**, estimates the Doppler shift in the C/A signals. At Block **1530**, the received code phases of the GPS C/A signals are then estimated using the estimated Doppler shifts that were obtained at Block **1520**. Finally, at Block **1540**, the estimated Doppler shifts and/or the estimated received code phases are transmitted by the mobile terminal, for example as part of the transmission of pseudo-range

measurements **1312**, to the network operations center (NOC) **1454** using the terrestrial base stations **1320** and/or the space-based component **1450**, over a satellite, terrestrial and/or other frequency band, as was described above. Accordingly, the estimated Doppler shifts (Block **1520**) are used to estimate the received code phases of the GPS

5   C/A signals (Block **1530**). This can reduce the amount of signal processing used to estimate the received code phases of the GPS C/A signals.

It will be understood that in some embodiments of the present invention, operations of Figure 15 may be performed by a mobile terminal that includes a GPS processor and a cellular data transceiver (but not a cellular voice transceiver) therein,

10   wherein the estimated Doppler shifts are used by a GPS processor to reduce the amount of signal processing to estimate the received code phases of the GPS C/A signals. In other embodiments of Figure 15, the mobile terminal may include a GPS receiver, a terrestrial cellular voice and data transceiver and/or a satellite cellular voice and data transceiver. In some of these embodiments, the mobile terminal may

15   be configured to operate in conjunction with an ancillary terrestrial network, as was described above.

Figure 16 is a flowchart of other operations that may be performed in the mobile terminal **1310** according to other embodiments of the present invention. These embodiments use GPS data, such as the GPS data **1322** of Figures 13 or 14,

20   that may be received from a wireless network, such as the terrestrial wireless networks of Figures 13 or 14 and/or a satellite wireless network, to allow the computations for computing the estimated code phases of the GPS signals to be reduced.

In particular, referring to Figure 16, at Block **1610**, the measured Doppler

25   shifts and measured code phases are received from the terrestrial and/or satellite wireless network. These parameters may be received as part of the GPS data **1322** that is conveyed from the terrestrial wireless network of Figures 13 or 14 and/or a satellite wireless network. At Block **1510**, the GPS C/A signals are received, as was already described. At Block **1620**, Doppler shifts in the GPS C/A signals are

30   estimated using the measured Doppler shifts and C/A code phases conveyed from the wireless network. Then, at Block **1630**, the code phases of the received GPS C/A signals are estimated using the estimated Doppler shifts of Block **1620**. Finally, at Block **1540**, the estimated Doppler shift and/or the estimated received code phases are

transmitted to the NOC. The NOC can compute a position fix and transmit the position of the mobile terminal to the mobile terminal.

It will be understood that in some embodiments of the present invention, operations of Figure 16 may be performed, for example, by a mobile terminal that

5   includes a GPS receiver, a terrestrial cellular transceiver and/or a satellite cellular transceiver for receiving the measured Doppler shifts and the measured code phases from a terrestrial wireless network. In still other embodiments, the operations of Figure 16 may be performed in connection with an ancillary terrestrial network, as was described above. In yet other embodiments, the operations of Figure 16 may be

10   performed in connection with a satellite and/or terrestrial wireless network, as was described above.

Some embodiments of the present invention can support both outdoor and in-building position reporting for mobile terminals 1310 communicating with a terrestrial base station 1320 such as an ATC and/or communicating with a satellite

15   wireless network using terrestrial and/or satellite wireless frequency bands. Some embodiments can exploit the relatively small size of the terrestrial network cells 1330 to reduce or minimize the computational requirements at the mobile terminal 1310, while reducing or minimizing the amount of pseudo-range data transferred to the NOC 1454. Some embodiments can preprocess the received GPS signals at the

20   mobile terminal 1310, which can enable further computational reductions.

Some embodiments of the present invention can be applied to any cellular network architecture and/or local and/or wide area network architecture, wherein the base stations can comprise terrestrial cellular network base stations, ancillary terrestrial network base stations and/or access points of a wireless local and/or wide

25   area network. In some embodiments, the cell sizes may be on the order of a few miles radius or less. Embodiments of the invention may also be used with cellular satellite-mode operation by providing mechanisms to determine the approximate location (for example within a few miles) of the mobile terminal within its assigned satellite beam. Two embodiments for estimating an approximate mobile terminal position within the

30   satellite beam will be described in detail below in connection with Figures 27-30.

In some embodiments of the invention, the Doppler shift and code phase of the received coarse/acquisition (C/A) signals 1342 from each GPS Satellite 1340, also referred to herein as a Space Vehicle (SV), are estimated at the mobile terminal 1310.

The small cell size can be taken advantage of to reduce the maximum *a priori* uncertainty in these parameters as follows:

Reduced Code Phase Range: The C/A code is a repeating 1023-chip Gold Code sequence with chip rate of 1.023 Mcps. Thus, the chip "length"

5   (relative to the speed of light) is 3.0e+8 m/s / 1.023e+6 = 293.26 meters. Approximating the cell coverage as a flat circle of radius R, then the maximum range variation to the SV, denoted "Δ", from the center of the cell to the cell edge is:

$$\Delta = R \cos(El), \text{ where El is the elevation angle to the SV.} \tag{1}$$

10   .   The code phase is the offset, in chip periods, of the received C/A Gold Code frame relative to the start of the frame, measured at a particular observation time. In this approach, each terrestrial base station, also referred to herein as a BTS, is equipped with a GPS receiver with which it can accurately measure the code phase of each C/A signal in view and download this information to

15   the mobile terminal. Referring to Equation (1), for the worst-case elevation angle of 0° and a typical cell radius R of 1000m, the value of Δ in terms of chip lengths is equal to 1000 / 293.26 = 3.41 chips. Since the BTS is typically located near the center of the cell, then the measured code phase at any location within the cell generally will lie within about ±4 chips of the code

20   phase measured at the BTS. Code phase range uncertainty is thereby reduced.

Reduced Doppler Shift Range: By similar analysis to the above, the precise Doppler shift of the received C/A signal due to SV motion (which generally is the largest contributor to Doppler shift) is also measured at the

25   BTS and downloaded to the mobile terminal. Because of the cell's small size compared to the distance to the GPS satellite, this Doppler shift component generally will be approximately the same for any location within the cell **1330**. Thus, the Doppler frequency search at the mobile terminal can be reduced to just a small range about this known SV Doppler component. Any residual

30   frequency offset (after subtracting out the SV Doppler shift), which may be referred to herein as "residual Doppler shift", will be primarily due to the Doppler shift caused by the motion of the mobile terminal, and may also possibly include any local oscillator frequency offset error and multi-path fading effects. This analysis assumes that the mobile terminal's local-

oscillator is sufficiently accurate so that down-conversion frequency errors can be ignored.

Assume an operating scenario where the mobile terminal is inside a moving vehicle with no direct line-of-sight to any SV, which may approximate the signal-to-noise ratio of the in-building case. Then, the maximum residual Doppler shift due to the vehicle motion should be accommodated. Given a vehicle velocity v (m/s), it can be shown that the maximum residual Doppler shift Δf_v due to vehicle motion is:

$$\Delta f_v \text{ (Hz)} = f_{source} \cdot (\pm v \, / \, C) \quad = 1.57542e+9 \cdot (\pm v \, / \, 3.0e+8) \qquad (2)$$

For a vehicle traveling at 60 mi/hr (26.8 m/sec) directly toward an SV located near the horizon (worst case), the Doppler shift due to vehicle motion $\Delta f_v =$ 141 Hz. Thus a residual Doppler search range of about ± 160 Hz should be accommodated for this case.

Figure 17 is a block diagram of operations that may be performed in a mobile terminal, such as a mobile terminal **1310**, according to some embodiments of the present invention. As shown in Figure 17, received GPS signals **1342**, that generally include noise, are received at a receiver RF section **1750** which may be part of a transceiver **1314**. At Block **1710**, a snapshot of time samples of the received GPS signals plus noise is collected, which may correspond to Block **1510** of Figure 15. At Block **1720**, the time samples are processed to estimate the Doppler shift of each received C/A signal, which may correspond to Block **1520** of Figure 15. At Block **1730**, the Doppler shift estimate from Block **1720** is used to reprocess the time samples to estimate the code phase of each received C/A signal, which may correspond to Block **1530** of Figure 15. The code phase estimate and Doppler shift estimate are then transmitted to the NOC at Block **1740**, which may correspond to Block **1540** of Figure 15. As will be described in detail below, the determination of the Doppler shift in Block **1720** can allow for computationally efficient calculation of C/A code phase in Block **1730**.

Upon collecting the received signal plus noise samples in Block **1710**, the mobile terminal transmits to the NOC (for example, via the BTS **1320**) the precise time at which the GPS signal samples in Block **1710** were measured. Using the SV ephemeris (carried by GPS signals **1342**), the NOC **1454** (for example via the BTS **1320**) informs the mobile terminal **1310** of which SVs **1340** were in view at the mobile terminal's approximate location at the time of its measurement in Block **1710**.

In some embodiments, before proceeding to Blocks **1720** and **1730**, the mobile terminal downloads the following information from the BTS **1320** for each C/A signal to be processed:

1. The Doppler frequency shift due to SV motion measured at the BTS,
5   corresponding to the mobile terminal's observation period. Since the BTS is not moving, this can simply be the total Doppler shift measured at the BTS. (See Block **1610**.)

2. The code phase measured at the BTS corresponding to the mobile terminal's measurement time. (See Block **1610**.)

10   3. The 50 bps ephemeris data bit sequence transmitted during the mobile's observation period. Each C/A signal is overlaid with 50 bps binary data whose bit transitions reverse the sign of the underlying Gold Code chips. Before the C/A signals are processed, the received samples are first multiplied by an exact replica of the 50 bps bit sequence to strip out this data modulation.
15   To reduce processing time and/or for the in-building case, where the SV signal strength may be too low to allow the mobile to recover the 50 bps data directly from the received C/A signals, this data may be downloaded to the mobile from the BTS.

Embodiments of Blocks **1710**, **1720** and **1730** in Figure 17 now will be
20   described in detail. Specific parameter values used herein are presently believed to be representative, based on computer simulation results.

Figure 18 is a block diagram illustrating detailed embodiments of Block **1710** of Figure 17. As shown in Figure 18, the C/A signals are received and amplified by the mobile terminal receiver's RF section, Block **1750**, then band-pass filtered at
25   Block **1810** to increase or maximize received signal-to-noise ratio. After filtering, the signals plus received noise may be down-converted to the complex baseband at Block **1820**, for example, using quadrature mixer components that separately down-convert the in-phase (I) and quadrature phase (Q) components. The baseband I and Q-outputs can be mathematically equated to a complex signal, for example, the complex
30   envelope of the received signal (hence the term "complex baseband"), where the I-component is the real part, and the Q-component is the imaginary part. It should be noted that, in some embodiments, from this point onward, the signal flow actually may be comprised of parallel I- and Q-paths. The received C/A signals plus noise may be further filtered at Block **1825** and time-sampled at Block **1830**, for example at

a rate of 1.024 MHz, and then quantized at Block **1840**, converting them from analog to discrete-time digital samples. Finally, a "snapshot" of received time samples "x(n)" is collected and stored in memory at Block **1850**. For the in-building environment, analysis has shown that about 1-million time samples may be needed to

5   reliably recover the weak C/A signals from the received noise. For this illustration, a total of 1.024 million complex time samples, representing exactly 1-second of observation time, are collected and stored in memory at Block **1850**.

        Figure 19 is a flowchart illustrating operations of Block **1720** of Figure 17 according to some embodiments of the present invention. As shown in Figure 19, in

10   these embodiments, residual Doppler shift estimation includes two operations. At Block **1910**, bandpass filtering of the received input samples x(n) into narrow frequency bands called "slices" is performed, and then the filtered, frequency-sliced samples are despread using an internally generated reference code matched to the received C/A code. Then, at Block **1920**, the residual Doppler shifts are estimated

15   from the slices that are despread.

        Figure 20 illustrates bandpass filtering GPS C/A signals into frequency slices, as was generally described in Block **1910** of Figure 19. More particularly, the one second snapshot x(n) of received signal plus noise samples from Block **1710** is first filtered by a bank of K bandpass filters, as illustrated in Figure 20. In some

20   embodiments, each filter has a bandwidth of, for example, approximately 32 kHz. Each filter passes a frequency band or "slice" of the received signal plus noise. The total number of slices K to be processed may depend on the signal-to-noise ratio of the input samples. For example, for an outdoor case with direct line of sight to the SVs, simulation results indicate that a single frequency slice centered at 0 Hz (in the

25   complex baseband) may be sufficient. For the indoor case where significant attenuation of the SV signals may exist, up to, for example, seven frequency slices (K=7) may be used to obtain an accurate estimate of the Doppler frequency. The filtering of input sequence x(n) into frequency slices may be performed once for all C/A signals to be processed.

30   Figure 21 is a block diagram of operations that may be performed in filtering and despreading the input samples (Block **1910** of Figure 19). These operations may be performed in parallel for each frequency slice. At Blocks **2010**, the 1.024 million complex received samples $x(n)$ from Block **1850** are first frequency-translated by

31

multiplication with complex sinusoid $e^{-j\omega_k n}$, $(1 \leq k \leq K)$, where ω_k is the center

frequency of the "k^{th}" frequency slice. Fourier Transform theory states that

multiplication of a signal by $e^{-j\omega_k n}$ in the time domain is equivalent to translating its

spectral components by an amount ω_k in the frequency domain. The frequency

5   translated sequences are passed through digital low-pass filters **2020** having a filter

bandwidth of, for example, ±16 kHz. A choice of filter bandwidth is explained

below. This filtering passes that part of the frequency content of the original $x(n)$

samples contained within a ±16 kHz frequency slice centered at frequency ω_k. The

filtered output is then down-sampled at Blocks **2030** using decimation-by-32,

10   resulting in a sequence **2040** containing, for example, 32000 complex elements for

each frequency slice. Down-sampling can greatly reduce the computations for the

downstream processes, in some embodiments of the invention.

      Still continuing with the description of Figure 21, for each C/A signal, the

receiver generates an internal reference code sequence **2050** set to the same Gold code

15   used by the received C/A signal. The reference code phase is synchronized to the

code phase of the C/A signal as measured at the local BTS. A very small timing

adjustment (a few parts per million or less), due to the SV-induced Doppler shift, may

be applied to the reference Gold Code sample period at Block **2050** to maintain

alignment with the received C/A code over the entire 1-second observation period.

20   For each slice, the internal reference code sequence **2050** is frequency-

translated by multiplication at Blocks **2060**, with complex sinusoid $e^{+j\omega_k n}$. Note that

the exponent $+j\omega_k n$ has the opposite sign from the translation $e^{-j\omega_k n}$ (Block **2010**)

applied to the input samples. This may be used so that the translation sinusoids $e^{-j\omega_k n}$

and $e^{+j\omega_k n}$ cancel each other when multiplied together later at Blocks **2090**. The

25   frequency-translated reference code samples are next low-pass filtered at Blocks **2070**

and down-sampled at Block **2080** using, for example, decimation by 32. This

produces a frequency "slice" of the reference code corresponding to that of the input

samples, but in the opposite frequency direction. Finally, the filtered received

sequence **2040** for each frequency slice is despread by multiplication at Block **2090**

30   with its corresponding filtered reference code to produce a despread output sequence

$y_k(n)$ $(1 \leq k \leq K)$ containing, for example, 32000 complex elements, as shown in Fig.

21.

It can be shown mathematically that the despread slice output sequence $y_k(n)$ in Figure 21 is given by:

$$y_k(n) = C\, d(n)\, e^{j[\omega_D n + \theta + \Delta\theta_k]} \text{ (+ higher frequency terms)}, [1 \le k \le K] \qquad (3)$$

where:

5     $d(n)$ = 50 bps data modulation overlay (± 1),

ω_D = received signal Doppler frequency,

C = a constant,

θ = a constant phase angle, and

$\Delta\theta_k$ = a variable phase angle component, proportional to the product of the

10   slice center frequency ω_k and the time offset between the received C/A code and internal reference code phases.

The "higher frequency terms" in Equation (3) are filtered out in subsequent processing, and therefore may not be relevant to the solution.

Accordingly, Figure 21 illustrates embodiments of the present invention where

15   the processor of the mobile terminal is configured to bandpass filter the GPS C/A signals into frequency slices by frequency translating the GPS C/A signals, low pass filtering the GPS C/A signals that are frequency translated and downsampling the low pass filtered, frequency translated GPS C/A signals. Figure 21 also illustrates embodiments of the present invention wherein the processor of the mobile terminal is

20   further configured to despread the frequency slices by generating an internal reference code sequence, frequency translating the internal reference code sequence for each frequency slice, low pass filtering the frequency translated reference code sequences, and multiplying by the downsampled low pass filtered, frequency translated GPS C/A signals.

25   A detailed description of the use of filtering prior to despreading, as was generally described in Figure 21, now will be provided. Specifically, the internally generated reference code 2050 in Figure 21 is synchronized to the received C/A code in order to despread the received signal 1850. However, the precise code phase of the received C/A signal is still unknown at this point, and may be several chips offset

30   from the internal reference code phase (which is synchronized to the code phase measured at the BTS). As explained below, both the input $x(n)$ and reference code may be filtered into narrow frequency "slices" to allow sufficient correlation between the two to enable despreading to occur.

The effect of the filtering is shown in Figure 22. In this figure, the autocorrelation of a 1023-chip Gold sequence with chip rate of 1.023 Mcps is plotted for several values of low-pass filtering. For a filter bandwidth of 511 kHz, the autocorrelation peak falls off to near-zero at an offset of one chip position, indicating

5   that two identical Gold sequences would be almost completely decorrelated with just one chip offset between them. When the filter bandwidth is reduced to 256 kHz, decorrelation occurs at an offset of about 2 chip periods. When the filter bandwidth is further reduced to 32 kHz, the auto-correlation peak becomes very broad, remaining relatively flat over an offset range of ±5 chip periods.

10   Recall that the reference code phase is set equal to the C/A code phase measured at the BTS. It was previously shown that the code phase measured at any location within a cell of 1 km radius may lie within about ±4 chip periods of the code phase measured at the BTS. Therefore, Figure 22 shows that the C/A code received at the mobile terminal, when filtered to a ±32 kHz bandwidth or narrower, can maintain

15   a high degree of correlation to the reference code (also filtered to the same bandwidth) for code phases that can be received within the coverage area of the cell.

A potential benefit of this filtering technique is that it can provide sufficient correlation between the received and reference codes to perform despreading, without having to do an exhaustive search to precisely align the two sequences. This can

20   significantly reduce the computational load for operations of Figure 21.

Figure 23 is a block diagram of operations that may be performed to estimate residual Doppler shifts from the slices that are despread, which may correspond to Block 1920 of Figure 19. These operations may be repeated for each received C/A signal. Referring now to Figure 23, the despread $y_k(n)$ 2090 are first multiplied by the

25   50 bps ephemeris data at Blocks 2310 to strip off the 50 bps modulation. The 50 bps data bit sequence may be supplied by the BTS to the mobile terminal. The samples are then multiplied at Blocks 2320 by the complex sinusoid $e^{-j\omega_{sv}n}$, where ω_{sv} is the received Doppler frequency component due to SV motion measured at the BTS. The multiplication at Block 2320 removes the SV-induced Doppler shift by frequency-

30   translating $y_k(n)$ by the negative of the SV Doppler frequency component. After this frequency translation, only the residual Doppler shift due to user motion may remain.

Still referring to Figure 23, the samples are next low-pass filtered at Blocks 2330 to a bandwidth of, for example, ±1 kHz to remove the higher frequency terms in

34

Equation (3), and down-sampled at Blocks **2335** by a factor of, for example, 64. The resulting sequences $z_k(n)$ Blocks **2340** contain, for example, 500 samples for each frequency slice. The $z_k(n)$ are "zero-padded", for example, to 2048 samples, and then Fast Fourier Transformed (FFT) at Blocks **2345** to the frequency domain. The

5 resulting complex frequency elements $Z_k(m)$ are converted to magnitude (or, in some embodiments, magnitude-squared) values at Blocks **2350**, and then added together across all K-frequency slices on a point-by-point basis at Block **2355**.

The frequency peaks corresponding to the residual Doppler frequency add coherently at Block **2355** since they occur at the same place for all slices. However,

10 random peaks caused by channel noise add non-coherently because the noise contained within the slices are uncorrelated (since the slices are assumed to not substantially overlap in frequency). Thus, the summation process across multiple frequency slices at Block **2355** can enhance the ratio of true Doppler peak to the false peaks caused by the channel noise. The frequency peak and several adjacent points

15 on either side are selected at Block **2360**, and then interpolated at Block **2365** using, for example, a parabolic best-fit to estimate the exact value of the residual Doppler shift ω_{MT} due to user motion **2370**. This value **2370**, when added to the SV-Doppler component ω_{sv} downloaded to the mobile terminal from the BTS, provides an estimate of total Doppler shift ω_D for the received C/A signal, which can be accurate

20 to within a fraction of a Hertz.

Accordingly, Figure 23 illustrates embodiments of the present invention wherein the processor is configured to estimate the Doppler shifts from the frequency slices that are despread by frequency-translating the frequency slices that are despread by the Doppler shift frequency that is measured at the wireless network to obtain the

25 residual Doppler shift due to mobile terminal motion, transforming the despread frequency-translated slices to the frequency domain (for example by fast-Fourier transform), converting complex frequency domain values to magnitude (and/or magnitude-squared) values, and adding the magnitude values on a point-by-point basis across the frequency slices.

30 Figure 24 is a block diagram of operations that may be performed to estimate the received code phase, which may correspond to Block **1730** of Figure 17. Referring to Figure 24, the received samples x(n) from Figure 18 are first multiplied at Block **2410** by the 50 bps ephemeris data sequence to strip off the data modulation.

The total Doppler shift is then removed by multiplying the received samples by the complex sinusoid $e^{j\omega_D n}$ at Block **2420**, where the frequency ω_D is the total Doppler shift comprised of the residual Doppler estimated in Figure 23, plus the SV-Doppler component downloaded from the BTS. A very small effect of the Doppler shift on the

5   received chip duration may also be compensated by first up-sampling the sequence by a factor of, for example, 8 at **2430**, and then adjusting the time scale of the samples periodically in 1/8-chip steps by incrementing or decrementing the tap delay output of the shift register **2440**. The resulting true baseband samples **2450** (having all Doppler shift removed in some embodiments) contain two components: a signal term

10   comprised of identical repeating Gold Code frames at a frame period of 1-msec., and a noise component. Successive 1-msec. segments are then summed at Block **2460** point-by-point to produce a single frame of, for example, 8192 sample points, thereby compressing, for example, the entire 1-second snapshot into a single equivalent 1-msec. frame. The signal components from each of the 1000 original segments **2450**

15   combine coherently, while the uncorrelated noise components combine non-coherently. This can produce a factor of 1000 (30 dB) improvement in the signal-to-noise ratio of the equivalent frame **2460**.

Still referring to Figure 24, the 1-msec. frame **2460** is then correlated with an internally generated reference code frame identical the received C/A Gold Code at

20   Block **2470**. The correlation at Block **2470** can be based on a Fast Fourier Transform (FFT) in some embodiments. This FFT can use the correspondence between multiplication in the frequency domain and convolution in the time domain to produce a very computationally efficient correlation in some embodiments. The complex output values from the correlation Block **2470** are converted to magnitude-squared

25   values at **2480**, and the location of the peak value corresponds to the code phase of the received C/A signal. The peak value **2490** together with several adjacent points on either side are interpolated at **2495**, for example by generating a least-squares-fit to a parabolic curve in the same manner as was done to interpolate the Doppler frequency at Block **2365**. The code phase value corresponding to the vertex of the parabola is

30   chosen as the final interpolated code phase estimate for the received C/A signal. Figure 25 graphically illustrates an embodiment of this interpolation.

Accordingly, Figure 24 illustrates embodiments of the present invention wherein the processor of the mobile terminal is configured to estimate the code phases

of the GPS C/A signals by removing a total Doppler shift by frequency-translating the GPS C/A signals by the sum of the residual Doppler shifts that are estimated plus the Doppler shift that is measured at the wireless network, summing segments of the GPS C/A signals from which the total Doppler shift has been removed, correlating the

5   summed segments with an internally generated code frame, and determining the time offset corresponding to the peak magnitude squared value.

Operations of Figures 21, 23, and 24 may be repeated for each C/A signal as was shown in Figure 17, and the resulting estimates of code phase and residual Doppler shift for each SV determined from Figures 23 and 24, respectively, are

10   transmitted from the mobile terminal to the NOC (Block 1740). At the NOC, they are combined with SV ephemeris and cell location information to generate a final position fix. The processing performed at the NOC may be similar to that used in conventional assisted-GPS methods, such as described in U.S. Patents 5,663,734 and/or 6,169,514, and need not be described further herein. The final position fix may

15   then be downloaded to the mobile terminal from the NOC and displayed to the mobile user.

In some embodiments of the invention, the complex frequency translation sinusoids $e^{j\omega_x n}$ shown in Figures 21, 23, and 24, where ω_x generically represents the specific translation frequencies given in the Figures, may in some cases be replaced

20   by complex sinusoidal approximations such as a square wave or other suitable periodic complex waveforms having frequency ω_x.

In some embodiments of the invention, the combination of removing the total Doppler shift (determined in Figure 23) and stripping off the 50 bps data modulation from the received input samples can enable the entire 1-second snapshot collected in

25   Figure 18 to be compressed down to an equivalent single 1-msec. code frame of 8192 points (Block 2460). This can greatly reduce the number of computations to implement the FFT-based correlation (Block 2470) in Figure 24 to determine the code-phase of the received C/A signals, according to some embodiments of the invention.

30   Other embodiments for determining the code phase of the received C/A signals now will be described. These embodiments can replace and/or be used with the embodiments described in Figure 24.

In particular, referring to the Doppler estimation in Figure 21, it was shown in Equation (3) that the despread outputs $y_k(n)$ for each of the K frequency slices contain a variable phase angle $\Delta\theta_k$ associated with the Doppler frequency term. It can be shown analytically that $\Delta\theta_k$ is related, to a very close approximation, to the difference

5   between the received C/A signal code phase and the internal reference code phase as follows:

$$\Delta\theta_k \quad = -\omega_k\Delta\tau \tag{4}$$

where:

ω_k = center frequency of "k^{th}" slice (radians/sec.), and

10     $\Delta\tau$ = received C/A signal code phase minus internal reference code phase (sec.).

Denote $\Delta\tau$ as the "residual code phase", because it represents the time difference between the code phase measured at the mobile terminal and the code phase measured at the local BTS (to which the mobile terminal's internal reference code is

15   synchronized).

Equation (3) shows that the Doppler frequency term in $y_k(n)$ also contains a constant phase angle θ that is the same for all frequency slices. Let θtot_k be the total phase angle of the Doppler frequency term in $y_k(n)$. Then from Equations (3) and (4):

20     $$\theta tot_k \quad = \theta + \Delta\theta_k \quad = \theta - \omega_k\Delta\tau. \tag{5}$$

The difference in total phase angle between the k^{th} and j^{th} frequency slices is given by:

$$\theta tot_k - \theta tot_j = \omega_j\Delta\tau - \omega_k\Delta\tau \quad = (\omega_j - \omega_k)\Delta\tau. \tag{6}$$

25

Equation (6) can be solved explicitly for the residual code phase $\Delta\tau$ as follows:

$$\Delta\tau \quad = -(\theta tot_k - \theta tot_j)/(\omega_k - \omega_j) \tag{7}$$

From Equation (7), it can be seen that if θtot_k is plotted versus slice center frequency

30   ω_k for all K frequency slices, the resulting points will align in a straight line whose slope is equal to the negative of the residual code phase $\Delta\tau$. In this way, $\Delta\tau$ can be determined as an extension of the Doppler shift estimation in Figure 23 with very little additional computational effort, in some embodiments of the invention. These

embodiments can represent a significant reduction in computations compared to the code phase estimation process described in Figure 24.

Figure 26 is a block diagram of these alternate embodiments to estimate the received code phase, which may also correspond to Block **1730** of Figure 17.

5 Referring to Figure 26, the phase $\phi_k(m)$ of the complex FFT output elements $Z_k(m)$ **2610** from Figure 23 are calculated at Blocks **2615** using the relation:

$$\phi_k(m) = \text{Arctan}[\text{Im}\{Z_k(m)\} / \text{Re}\{Z_k(m)\}], \qquad (8)$$

10 where $\text{Im}\{Z_k(m)\}$ and $\text{Re}\{Z_k(m)\}$ are imaginary and real parts of $Z_k(m)$, respectively. The resulting phase values $\phi_k(m)$ **2620** are interpolated at Blocks **2630** to determine the phase angle $\phi_k(\omega_D)$ corresponding to the precise Doppler shift frequency ω_D determined in Figures 23 and 24. The $\phi_k(\omega_D)$ values as a function of slice center frequency ω_k are least-squares fit to a straight line at Block **2640**. Since the range of

15 $\phi_k(\omega_D)$ values may vary by more than 2π radians, this operation may involve "unwrapping" the $\phi_k(\omega_D)$ terms by adding or subtracting multiples of 2π so that the results fall in an unbroken straight line over all slice frequencies ω_k. The residual code phase $\Delta\tau$ is then determined as the negative slope of the linear best-fit to the $\phi_k(\omega_D)$ vs. ω_k data points. Finally, the total code phase estimate for the given C/A signal is

20 equal to the residual code phase $\Delta\tau$ plus the internal reference code phase (i.e., the code phase measured at the local BTS).

Accordingly, Figure 26 illustrates other embodiments of the present invention, wherein the processor of the mobile terminal is configured to estimate the code phases of the GPS C/A signals by calculating phases of the frequency slice values that have

25 been converted to the frequency domain, determining phase angles corresponding to the estimated Doppler shift frequency for each of the slices, and determining a residual code phase from the phase angles.

Embodiments of the invention that were described above assume that the received C/A signal code phase at the mobile terminal is within a relatively small

30 number of chips offset from the code phase measured at the local BTS. This may constrain the maximum distance between the mobile and BTS to the order of a few miles. This potential constraint may not pose a problem in a terrestrial cellular network (conventional and/or ATC-based) where the cell radius may typically be on

the order of or less than one mile. However, in a satellite network, a satellite beam coverage may extend over hundreds of miles, which may far exceed the assumed maximum distance. Consequently, it may be desirable for the satellite network to be able to estimate the location of the mobile terminal to within, for example, a few

5   miles uncertainty inside its beam, and then transmit to the mobile the pertinent C/A code phase and Doppler information referenced to the mobile's estimated location. Using this information, the mobile terminal can then proceed to measure the precise C/A code phase and Doppler shift as described above. Two embodiments for determining the mobile terminal's approximate location within a satellite beam will

10   now be described.

In general, in first embodiments, the mobile terminal's approximate location within a satellite beam is determined by measuring relative differences in received signal levels between adjacent satellite beams at the mobile terminal. In second embodiments, the mobile terminal's approximate location within a satellite beam is

15   determined by measuring path delays between the mobile terminal and a satellite gateway via at least two satellites.

More specifically, the first embodiments compare signal levels from adjacent beams and may be suitable when satellite coverage includes multiple spot beams with coverage overlap between adjacent beams. In these embodiments, the signal levels

20   received in the mobile terminal's assigned spot beam as well as the immediately adjacent beams are compared, and an estimate of the mobile terminal's location is determined by analyzing the relative differences in received signal levels between the beams.

Figure 27 graphically illustrates an example of a typical spot beam antenna

25   pattern. The pattern generally is short-term invariant and is assumed to be known to the satellite network.

Consider a mobile terminal located within the spot beam coverage map of Figure 28. The mobile terminal transmits a signal to the satellite, which is simultaneously received at the satellite gateway over the mobile terminal's assigned

30   beam and, for example, six adjacent beams. The received signal levels vary between the beams, due to the different spot beam gains that occur at distances $d1$ through $d7$ from the mobile terminal to each beam center. The NOC measures these signal levels and makes an initial guess as to the radial distance $d1$ from the mobile terminal to the center of its assigned beam. Then, the spot beam gain corresponding to radial

distance **d1** is calculated using the known spot beam pattern data, such as that shown in Figure 27. The differences in measured signal levels between the mobile terminal's assigned beam and adjacent beams are then used to produce spot beam gain estimates for beams 2 through 7, which in turn produce estimates of radial distances **d2** through

5   **d7** for the adjacent beams.

As shown in Figure 29, circles of radius **d1** through **d7** centered on their respective spot beams are projected onto the coverage map. These circles represent contour lines of the spot beam gains that were estimated from the signal measurements. If the contour circles do not intersect at at least one common point, a

10   new radial distance **d1** is chosen and the above operations may be repeated iteratively. When all the contour circles intersect, the area of intersection represents the mobile terminal's estimated location. This case is illustrated in Figure 29.

As an alternate embodiment to the above, the mobile terminal may measure multiple signals received from the satellite gateway over each of the beams in Figure

15   28. For example, a satellite network typically broadcasts a common control channel in each beam. The mobile terminal can make near-simultaneous measurements of the received control channel level in each beam, and transmit this information over the satellite link to the NOC. The NOC then can use the same operations described above to estimate the mobile terminal's location by finding an intersection region of the

20   estimated spot beam gain contour circles as illustrated in Figure 29.

As noted above, second embodiments can use multi-satellite diversity. These embodiments may be more suitable when two or more satellites are used to provide transmission path diversity for the network. The path distances between the satellites and the gateway station may be assumed to be known precisely by the network. The

25   satellite gateway broadcasts a periodic time mark to all mobile terminals in the network over one of the satellites. The mobile terminal receives the time mark, and after a fixed wait time known to the network, transmits a response signal back to the gateway. The response signal is simultaneously received at the gateway over the plurality of diversity satellites. The total elapsed time from transmission of the time

30   mark to reception of the mobile terminal response signal over each of the satellite paths is measured. The fixed wait time at the mobile terminal, as well as the satellite's internal transmission delay and any other fixed delays are subtracted out. The remaining times represent the round-trip path delays from gateway to mobile terminal and back to gateway for each satellite.

By knowing the speed of light and the precise distances from the gateway station to the satellites, the path distance "Pn" between satellite "n" and the mobile terminal can be estimated for each satellite. The set of equidistant points at a distance "Pn" from satellite "n" forms a spherical surface of radius Pn centered at satellite "n".

5   The intersection of this spherical surface with the surface of the earth forms an arc on the earth's surface. The mobile terminal is constrained to lay somewhere on or very close (accounting for altitude uncertainties) to this arc. The arcs produced by the plurality of satellites are offset from each other due to their different satellite orbital locations, and therefore intersect each other at a finite number of points.

10   Figure 30 illustrates the ranging position arcs produced by two diversity satellites, superimposed on the coverage area of the mobile terminal's assigned beam. The intersection of the two arcs is chosen as the estimate of the mobile terminal's location.

After the mobile terminal's location within its satellite beam has been
15   estimated using one of the two embodiments described above and/or other embodiments, the SV code phase, Doppler shift, and 50 bps ephemeris data sequence that would be observed from that location are transmitted to the mobile terminal. However, unlike the terrestrial cellular network, there may be no local BTS to measure these parameters directly. Instead, the satellite network may have complete
20   knowledge of the positions, velocities, and directions of all SVs in view at the time of the mobile's measurement, as well as their code phases and 50 bps data sequences. With this information, the NOC can calculate the code phase, Doppler shift, and 50 bps data bit transition times projected to any given observation point on the earth, replacing the direct measurement performed by the terrestrial BTS. The mobile
25   terminal uses this information supplied by the satellite network to perform its SV code phase and Doppler shift measurements, as was previously described for the terrestrial case.

As will be appreciated by one of skill in the art, the present invention may be embodied as a method and/or an apparatus. The present invention may take the form
30   of an entirely hardware embodiment, an entirely software embodiment or an embodiment combining software and hardware aspects. Furthermore, the present invention may be embodied as a computer program product on a digital storage medium having computer-readable instructions embodied in the medium. Any suitable digital storage medium may be utilized, including a memory device, hard

42

disk, CD-ROM, optical storage device, transmission medium, such as a wireless transmission medium and/or those supporting the Internet or an intranet, and/or a magnetic storage device.

The present invention was described with reference to block diagrams and/or flowchart illustrations of methods, apparatus (systems), mobile terminals, and/or computer program products according to embodiments of the invention. It is understood that a block of the block diagrams and/or flowchart illustrations, and combinations of blocks in the block diagrams and/or flowchart illustrations, can be implemented by computer program instructions. These computer program instructions may be provided to a processor of a general purpose computer, special purpose computer, a Digital Signal Processor (DSP) and/or other programmable data processing apparatus to produce a machine, such that the instructions, which execute via the processor of the computer and/or other programmable data processing apparatus, create means for implementing the functions/acts specified in the block diagrams and/or flowchart block or blocks.

These computer program instructions may also be stored in a computer-readable memory that can direct a computer, DSP, or other programmable data processing apparatus to function in a particular manner, such that the instructions stored in the computer-readable memory produce an article of manufacture including instructions which implement the function/act specified in the block diagrams and/or flowchart block or blocks.

The computer program instructions may also be loaded onto a computer, DSP, or other programmable data processing apparatus to cause a series of operational steps to be performed on the computer or other programmable apparatus to produce a computer-implemented process such that the instructions which execute on the computer or other programmable apparatus provide steps for implementing the functions/acts specified in the block diagrams and/or flowchart block or blocks.

It should also be noted that in some alternate implementations, the functions/acts noted in the blocks may occur out of the order noted in the flowcharts. For example, two blocks shown in succession may in fact be executed substantially concurrently or the blocks may sometimes be executed in the reverse order, depending upon the functionality/acts involved.

In the drawings and specification, there have been disclosed typical preferred embodiments of the invention and, although specific terms are employed, they are

43

used in a generic and descriptive sense only and not for purposes of limitation, the scope of the invention being set forth in the following claims.